



# East Electrical Supply Inc.

Specification Sheet - 2023-5

---

## 3" x 2" Gangable Switch Boxes (2 1/2" Deep)

3" x 2" Switch boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices. Switch boxes are used to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions. The adjustable plaster ears allow for an easy "cut in" when switches or outlets need to be added.

### Features

- Boxes – 2-1/2" deep
- Boxes – 12.5 cu in.
- Available with adjustable plaster ears, NM Clamps, brackets, MC Clamps where noted
- Gangable

### Standard Materials

- Galvanized Steel



**3" x 2" Gangable Switch Boxes (2 1/2" Deep)**

<b>Part No.</b>	<b>Description</b>	<b>Knockouts</b>	<b>Cubic Inches</b>	<b>Master Case Qty</b>
SBG500-50	3"X2" SW BX 2-1/2" DEEP 1/2" KO	Sides: (4) - 1/2" Ends: (2) - 1/2" Bottom: (2) - 1/2"	12.5	50
SBG503-50	3"X 2" SW BX 2-1/2" DEEP ECCENTRIC KO	Sides: (2) - 1/2" Ends:(2) - ECC 1/2" & 3/4" Bottom: (2) - 1/2"	12.5	50
SBG518-50	3"X 2" SW BX 2-1/2" DEEP MC CLAMP 1/2" KO	Sides: (4) - 1/2" Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	12.5	50
SBG519-50	3"X 2" SW BX 2-1/2" DEEP NM CLAMP 1/2" KO	Sides: (4) - 1/2" Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	12.5	50
SBG523-50	3"X 2" SW BX 2-1/2" DP MC CLMP OLDWRK 1/2" KO	Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	12.5	50
SBG524-25	3"X 2" SWBX 2-1/2" DP MC CLMP 1/2" KO-FL BRKT	Sides: (2) - 1/2" Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	12.5	50

