



# East Electrical Supply Inc.

Specification Sheet - 2023-5

---

## 4" x 2" Drawn Handy Boxes (1-7/8" Deep)

Handy boxes, also referred to as utility boxes, are used for switch boxes, convenience outlets or small junction boxes in exposed work applications. Great for appliances and machinery. Topaz handy utility boxes have a small, rectangular design that enables power outlets and switches to be installed in small places. Can easily be customized with special holes or knockouts for OEM applications.

### Features

- Drawn
- 1-7/8" deep
- 13.5 cubic inches
- Available in multiple KO sizes, with or without Concentric KOs and raised ground emboss with installed 10/32 ground screw where noted

### Standard Materials

- Galvanized Steel



**4" x 2" Drawn Handy Boxes (1-7/8" Deep)**

| <b>Part No.</b> | <b>Description</b>                               | <b>Knockouts</b>   | <b>Cubic Inches</b> | <b>Master Case Qty</b> |
|-----------------|--|--|---------------------|------------------------|
| H4450-50        | 4"X2" RECT BX STL<br>GSB 1-7/8" DP 1/2"<br>KO    | Sides: (8) - 1/2"<br>Bottom: (2) -<br>1/2"                                 | 13.5                | 50                     |
| H4451-50        | 4"X2" RECT BX<br>STL.1-7/8" DP 1/2"<br>KO        | Sides: (8) - 1/2"<br>Bottom: (3) -<br>1/2"                                 | 13.5                | 50                     |
| H4452-50        | 4"X2" RECT BX STL<br>1-7/8" DP 1/2" &<br>3/4" KO | Sides: (4) - 1/2"<br>& (4) - 3/4"<br>Bottom: (2) -<br>1/2" & (1) -<br>3/4" | 13.5                | 50                     |
| H4453-50        | 4"X2" RECT BX<br>STL.GSB 1-7/8" DP<br>3/4" KO    | Sides: (6) - 3/4"<br>Bottom: (1) -<br>3/4"                                 | 13.5                | 50                     |
| H4454-50        | 4"X2" RECT BX<br>STL.1-7/8" DP 3/4"<br>KO        | Sides: (6) - 3/4"<br>Bottom: (2) -<br>3/4"                                 | 13.5                | 50                     |
| H4456-50        | 4"X2" RECT BX<br>STL.1/2" & 3/4"<br>CONC 4-SD KO | Sides: (6) - 1/2"<br>& 3/4" CON<br>Bottom: (2) -<br>3/4"                   | 13.5                | 50                     |



H4450BC-C001