



4" x 2" Drawn Handy Boxes (2-1/8" Deep)

Handy boxes, also referred to as utility boxes are used for switch boxes, convenience outlets or small junction boxes in exposed work applications Great for appliances and machinery Topaz handy utility boxes have a small, rectangular design that enables power outlets and switches to be installed in small places Can easily be customized with special holes or knockouts for OEM applications

Features

- Drawn
- 2-1/8" deep
- 31 cu. in.
- Available in multiple KO sizes and raised ground emboss with installed 10/32 ground screw

Standard Materials

- Galvanized Steel



4" x 2" Drawn Handy Boxes (2-1/8" Deep)



Part No.	Description	Knockouts	Cubic Inches	Master Case Qty
H4467-50	4"X2" RECT BX 2-1/8" DEEP 1/2" & 3/4" KO	Sides: (4)-1/2" & (4)-3/4" Bottom: (1)-1/2" & (1)-3/4"	31	50
H4468-50	4"X2" RECT BX 2-1/8" DEEP 1/2" KO	Sides: (8)-1/2" Bottom: (2)-1/2"	31	50