EAST ELECTRICAL SUPPLY INC

Specification Sheet - 2025-2

3" x 2" Gangable Switch Boxes (3 1/2" Deep)

3" x 2" Switch boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices Switch boxes are used to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions The adjustable plaster ears allow for an easy “cut in” when switches or outlets need to be added

Features

- Boxes – 3-1/2" deep
- Boxes – 18 cu in.
- Pre-assembled with 10-32 ground screw & 7-1/2" Long #12AWG solid pigtail
- Available in multiple KO sizes with adjustable plaster ears, brackets, NM Clamps, and MC Clamps where noted
- Gangable

Standard Materials

- Galvanized Steel

3" x 2" Gangable Switch Boxes (3 1/2" Deep)

Partno	Item Description	Knockouts	Cubic Inches	Master Case Qty
SBG591-25	3"X 2" SW BX 3-1/2" DEEP ECCENTRIC KO	Sides: (4) - 1/2" Ends: (2) - 1/2", & (2) - 1/2" & 3/4" ECC Bottom: (2) - 1/2"	18	50
SBG600-25	3"X 2" SWBX 3-1/2" DP MC CL #12AWG PT 1/2" KO	Sides: (4) - 1/2" Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	18	50
SBG601-25	3"X 2"SWBX 3-1/2" DP NM CL #12AWG PT 1/2"KO	Sides: (4) - 1/2" Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	18	50
SBG604-25	3"X 2" SWBX 3-1/2" DP MC CL #12AWG PT-FL-BRKT	Sides: (4) - 1/2" Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	18	50
SBG605-25	3"X2" SWBX 3-1/2" DP NM CL #12AWG PT-FL-BRKT	Sides: (4) - 1/2" Ends: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	18	50

c UL us LISTED

© 2025 East Electrical Supply