



# East Electrical Supply Inc.

Specification Sheet - 2023-5

---

## 4" Octagon Drawn Boxes w/ Brackets & Supports

4" octagon junction boxes are used to install ceiling and wall lighting fixtures, or convenience outlets and devices. Octagon boxes are used to bring power to an electrical device where multiple conductor runs are split in two or more directions.

### Features

- Drawn
- 1-1/2" deep
- 15.8 cu. in.
- Available with multiple KO sizes, and various clamps and brackets
- Adjustable bar hanger lengths 14-1/4" to 22-1/2"

### Standard Materials

- Galvanized Steel



**4" Octagon Drawn Boxes w/ Brackets & Supports**

Part No.	Description	Knockouts	Cubic Inches	Master Case Qty
G3450-25	4" OCT BOX W/FL BRKT 1-1/2" DP 1/2" & 3/4" KO	Sides: (1) - 1/2" (2) - 1/2" & 3/4" CON Bottom" (3) - 1/2" & (2) - 3/4"	15.8	50
G3451-25	4" OCT BOX MC CLAMP- ADJ BAR HGR 1-1/2" DP	Sides: (2) - 1/2" & 4 pryouts	15.8	50
G3452-25	4" OCT BOX NM CLAMP- ADJ BAR HGR 1-1/2" DP	Sides: (2) - 1/2" & 4 pryouts	15.8	50
G3454-25	4" OCT BOX 1-1/2" DP -J WOOD BRKT, NM CLAMP	Sides: (1) 1/2" & 4 pryouts Bottom: (1) 1/2"	15.8	30
G3455-25	4" OCT BOX 1-1/2" DP MC CLAMP W/ FL BRACKET	Sides: (1) 1/2" Bottom: (1) 1/2"	15.8	50

