

EAST ELECTRICAL SUPPLY INC

Specification Sheet - 2025-2

4" Square Drawn Boxes


4" square drawn junction boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices. Square boxes are used to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions

Features

- Drawn
- 1-1/4" and 1-1/2" Deep
- Available in multiple KO sizes with raised ground emboss with installed 10/32 ground screw and pigtail where noted

Standard Materials

- Galvanized Steel

4" Square Drawn Boxes					
Partno	Item Description	Knockouts	Cubic Inches	Master Case Qty	
B4450-50	4" SQ BOX STL GSB 1-1/2" DP 1/2" KO 21.CU	Sides: (12) - 1/2" Bottom: (4) - 1/2"	21	50	
B4451-50	4" SQ BOX STL 1-1/2" DP 1/2" KO	Sides: (12) - 1/2" Bottom: (5) - 1/2"	21	50	
B4452-50	4" SQ BOX STL 1-1/2" DP 3/4" KO	Sides: (8) - 3/4" Bottom: (3) - 1/2" & (2) - 3/4"	21	50	
B4453-50	4" SQ BOX STL 1-1/2" DP 1/2" & 3/4" KO	Sides: (8) - 1/2" & (4) - 3/4" Bottom: (3) - 1/2" & (2) - 3/4"	21	50	
B4454-50	4" SQ BOX STL 1-1/2" DP 1/2" & 3/4" CON KO	Sides: (8) - 1/2" & 3/4" Con Bottom: (2) - 1/2" & (2) - 3/4"	21	50	
B8548-25	4" SQ BOX MC CLAMP-S-BRKT 1-1/2" DP ECC KO	Sides: (3) - 1/2" & (1) - 1/2" & 3/4" Ecc & 4 pryouts Bottom: (1) - 1/2"	22	50	

