

# EAST ELECTRICAL SUPPLY INC

Specification Sheet - 2025-2

## 4" Square Single Gang Device Rings

4" single gang device rings are used with 4" square boxes to mount switches, receptacles and devices C7515 flat surface is keyed to catch plaster or drywall mud

### Features

- Ideal for exposed work applications, providing an easy method for the installation of electrical devices
- Can be used on any 4" square box

### Standard Materials

- Galvanized Steel

| 4" Square Single Gang Device Rings |   |           |              |        |                 |  |
|------------------------------------|---|-----------|--------------|--------|-----------------|--|
| Partno                             | Item Description                          | Knockouts | Cubic Inches | Depth  | Master Case Qty |  |
| C4450-50                           | 4" SQ STL RING FLAT 1 GANG                | N/A       | N/A          | N/A    | 200             |  |
| C4452-50                           | 4"SQ STL RING RAISED 1/4" 1-GANG 1.7CU    | N/A       | 1.7          | 1/4"   | 200             |  |
| C4453-50                           | 4"SQ STL RING RAISED 1/2" 1-GANG 3.5CU    | N/A       | 3.5          | 1/2"   | 100             |  |
| C4454-50                           | 4"SQ STL RING RAISED 5/8" 1-GANG 4.5CU    | N/A       | 4.5          | 5/8"   | 100             |  |
| C4455-50                           | 4"SQ STL RING RAISED 3/4" 1-GANG 5.5 CU   | N/A       | 5.5          | 3/4"   | 100             |  |
| C4456-25                           | 4"SQ STL RING RAISED 1" 1-GANG 7.46 CU    | N/A       | 7.5          | 1"     | 60              |  |
| C4457-25                           | 4"SQ STL RING RAISED 1-1/4" 1-GANG 9.4 CU | N/A       | 9.4          | 1 1/4" | 50              |  |
| C4458-25                           | 4"SQ STL RING RAISED 1-1/2" 1-GANG 11.3CU | N/A       | 11.3         | 1 1/2" | 50              |  |
| C4459-25                           | 4"SQ STL RING RAISED 2" 1-GANG 14.5 CU    | N/A       | 14.5         | 2"     | 50              |  |

