

Specification Sheet - 2024-10

Multi-Gang Switch Boxes

Use when more than two devices or outlets are required in one box Multi-Gang switch boxes can be installed in walls or ceilings for lighting fixtures. Use to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions.

Features

- 1 5/8" Deep
- Welded
- Available with 1/2" and 3/4" concentric KO's
- Available in 2 thru 8 gangs

Standard Materials

Galvanized Steel

Multi-Gang Switch Boxes						
	Partno	Item Description	Knockouts	Cubic Inches	Depth	Master Case Qty
600	MSB13	1 5/8" Deep, 3 gang	Sides: (14) - 1/2" & 3/4" CON Bottom: (6) - 1/2" & (4) - 3/4"	58.5	1 5/8"	20
	MSB14	1 5/8" Deep, 4 gang	Sides: (16) - 1/2" & 3/4" CON Bottom: (6) - 1/2" & (4) - 3/4"	71	1 5/8"	20
	MSB15	1 5/8" Deep, 5 gang	Sides: (18) - 1/2" & 3/4" CON Bottom: (6) - 1/2" & (4) - 3/4"	81	1 5/8"	10

