



4" Octagon Drawn Boxes & Extensions

4" octagon junction boxes are used to install ceiling and wall lighting fixtures, fans or convenience outlets and devices. Octagon boxes are used to bring power to an electrical device where multiple conductor runs are split in two or more directions.

Features

- Drawn
- 1-1/2" deep
- 15.8 cu. in.
- Available in multiple KO sizes, with or without Concentric KOs and raised ground emboss with installed 10/32 ground screw where noted

Standard Materials

- Galvanized Steel

4" Octagon Drawn Boxes & Extensions				
Partno	Description	Knockouts	Cubic Inches	Master Case Qty
G2450-50	4" OCT BOX MC CLAMP 1-1/2" DP 1/2" KO	Sides: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	15.8	50
G2451-50	4" OCT BOX NM CLAMP 1-1/2" DP 1/2" KO	Sides: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	15.8	50
G2453-50	4" OCT BOX 1-1/2" DP- NM CLAMPS-EARS	Sides: (2) - 1/2" & 4 pryouts Bottom: (1) - 1/2"	15.8	50
G4451-50	4" OCT BOX STL 1-1/2" DP 3/4" KO	Sides: (4) - 1/2" Bottom: (4) - 1/2"	15.8	50
G4452-50	4" OCT BOX STL 1-1/2" DP 3/4" KO	Sides: (4) - 3/4" Bottom: (3) - 1/2" & (2) - 3/4"	15.8	50
G4453-50	4" OCT BOX STL 1-1/2" DP 1/2" & 3/4" KO	Sides: (2) - 1/2" & (2) - 3/4" Bottom: (5) - 1/2"	15.8	50
G4454-50	4" OCT BOX STL GSB 1/2" & 3/4" KO	Sides: (2) - 1/2" & (2) - 3/4" Bottom: (2) - 1/2" & (2) - 3/4"	15.8	50
G4455-50	4" OCT BOX STL GSB 1/2" & 3/4" ECC 4SD KO	Sides: (4) - 1/2" & 3/4" CON Bottom: (2) - 1/2" & 3/4" CON (2) - 1/2"	15.8	50

